



## EN MOUNTING INSTRUCTIONS

# RUSSELL – LED RUSSELL – LED – DALI IP65

### 1) Dimensions of the luminaire:




Type of luminaire	Power (W)	Ø (mm)	H1 (mm)	H2 (mm)	Weight (kg)
RUSSELL-LED-14500 (DALI)	103	340	187	255	6,5
RUSSELL-LED-22000 (DALI)	162	400	197	282	8
RUSSELL-LED-19000 (DALI)	146	340	187	255	6,5
RUSSELL-LED-26500 (DALI)	197	400	197	282	8

Number of luminaires on a MCB	B10	B16	C10	C16
RUSSELL-LED-14500	2	4	4	7
RUSSELL-LED-19000	2	4	4	7
RUSSELL-LED-22000	1	2	2	3
RUSSELL-LED-26500	1	2	2	3

### 2) Dimensions of surface mounts:

**RUSSELL – LED – 14500/19000 (DALI) / RUSSELL – LED – 19000/26500 (DALI)**





### 3) Possibilities for installation: Ceiling installation

a) suspended mount

b) surface mount


### 4) Possibilities for installation: Wall installation

c) surface mount



### 5) Montážní polohy při montáži pomocí výložníku

### 5) Mounting positions for surface mounting



## Upozornění pro montáž svítidla RUSSELL – LED

### Warning for mounting lighting fixture RUSSELL – LED



/EN/ Producer included in the recycling system provided by EKO-KOM company. (EK-F06070058)

/EN/ The lighting fixture can be installed by authorized persons only according to valid regulations on professional qualifications in electrical engineering. Failure to comply with manufacturer's installation instructions not liable for any damages!

/EN/ Construction of the lighting fixture doesn't need special maintenance. Wash the polluted housing with the cool water and detergent.

/EN/ In case of instruction non-performance producer can't be responsible for relevant damages caused!

/EN/ When the lighting installation you should follow ESD safety aids worth using!

/EN/ The luminaire is equipped with 2m supply cable with diameter 7mm and cable cross section is 3x1,5mm².

/EN/ The light source in this luminaire is non-replaceable.

#### Mounting instruction:

- 1) Take the lighting fixture from transport packing.
- 2) Fix the luminaire:
  - a) Suspended mount (picture 1)
  - b) Surface mount (picture 2)
- 3) Connect supply cable as follows:




#### RUSSELL – LED

phase wire      L1   - brown  
 neutral wire    N   - blue  
 protective wire Ⓢ - green-yellow

#### RUSSELL – LED – DALI

phase wire      L1   - brown  
 Neutral wire    N   - blue  
 protective wire Ⓢ - green-yellow  
 2-core cable for dimming  
 DIM +        -        blue  
 DIM -        -        white

Picture 1



Picture 2

